

RTU3-I.200HE-18-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100					956 / 0.57	1060 / 0.73	1155 / 0.89	1243 / 1.06	1325 / 1.24	1403 / 1.43	1477 / 1.62	1545 / 1.82	1611 / 2.03	1674 / 2.25	1735 / 2.47	1792 / 2.70
1500					994 / 0.72	1091 / 0.92	1182 / 1.13	1267 / 1.34	1348 / 1.56	1423 / 1.77	1496 / 2.00	1566 / 2.23	1632 / 2.46	1695 / 2.70	1756 / 2.94	1816 / 3.19
1900				963 / 0.69	1055 / 0.90	1143 / 1.12	1225 / 1.36	1305 / 1.61	1381 / 1.87	1453 / 2.12	1522 / 2.39	1590 / 2.66	1654 / 2.93	1716 / 3.20	1777 / 3.48	1836 / 3.77
2300			967 / 0.71	1053 / 0.91	1134 / 1.13	1212 / 1.37	1288 / 1.63	1360 / 1.90	1429 / 2.18	1497 / 2.48	1562 / 2.77	1627 / 3.08	1687 / 3.39	1748 / 3.71	1807 / 4.03	1862 / 4.35
2700	919 / 0.59	999 / 0.79	1078 / 0.99	1153 / 1.20	1226 / 1.44	1296 / 1.69	1364 / 1.96	1431 / 2.25	1494 / 2.55	1557 / 2.86	1618 / 3.19	1677 / 3.52	1735 / 3.87	1792 / 4.22	1847 / 4.57	
3100	1055 / 0.89	1125 / 1.12	1194 / 1.35	1262 / 1.58	1327 / 1.83	1391 / 2.10	1453 / 2.38	1513 / 2.68	1572 / 3.00	1630 / 3.33	1686 / 3.67	1741 / 4.02	1795 / 4.39	1847 / 4.75		
3500	1191 / 1.28	1253 / 1.55	1315 / 1.80	1376 / 2.06	1435 / 2.33	1493 / 2.61	1549 / 2.90	1605 / 3.21	1659 / 3.54	1712 / 3.88	1764 / 4.24	1815 / 4.60	1867 / 4.99			
3900	1327 / 1.77	1382 / 2.07	1439 / 2.35	1494 / 2.64	1548 / 2.93	1600 / 3.23	1653 / 3.54	1704 / 3.87	1754 / 4.20	1803 / 4.56	1852 / 4.92					
4300	1463 / 2.38	1514 / 2.70	1564 / 3.02	1615 / 3.33	1664 / 3.65	1713 / 3.97	1761 / 4.30	1808 / 4.64	1855 / 5.00							
4700	1599 / 3.11	1645 / 3.46	1692 / 3.81	1738 / 4.15	1784 / 4.50	1829 / 4.84										
5100	1735 / 3.97	1778 / 4.35	1821 / 4.74													

Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.

- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00312ET3H213T-S has an rpm range of 900 to 1150.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 900 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DHP0026 has an rpm range of 900 to 1150.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0026 has an rpm range of 900 to 1150.
- Motor DTP0034 has an rpm range of 900 to 1755.
- Motor DTP0034-50HZ has an rpm range of 900 to 1438.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP0026 has an rpm range of 900 to 1150.
- Motor GP0034 has an rpm range of 900 to 1800.
- Motor GP0034-50 has an rpm range of 900 to 1440.
- Motor GP0054 has an rpm range of 900 to 1800.
- Motor GP0054-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.
- Motor NP0026 has an rpm range of 900 to 1150.
- Motor NP0054 has an rpm range of 900 to 1745.