

RTU3-I.200HE-20-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100				1050 / 0.97	1202 / 1.40	1337 / 1.87	1459 / 2.38	1571 / 2.92	
1650			910 / 0.80	1086 / 1.25	1236 / 1.74	1369 / 2.28	1491 / 2.84	1602 / 3.44	1705 / 4.06
2200			968 / 1.06	1131 / 1.58	1276 / 2.15	1407 / 2.76	1527 / 3.40	1637 / 4.06	1739 / 4.75
2750			1048 / 1.40	1192 / 1.99	1327 / 2.63	1452 / 3.31	1568 / 4.02	1676 / 4.77	1778 / 5.54
3300		1015 / 1.30	1146 / 1.87	1272 / 2.51	1393 / 3.20	1508 / 3.95	1618 / 4.73	1721 / 5.55	
3850	1018 / 1.28	1142 / 1.85	1257 / 2.47	1367 / 3.16	1475 / 3.91	1580 / 4.72	1681 / 5.56	1778 / 6.44	
4400	1163 / 1.91	1274 / 2.55	1375 / 3.24	1474 / 3.99	1570 / 4.79	1665 / 5.64	1757 / 6.54		
4950	1309 / 2.73	1407 / 3.43	1500 / 4.19	1589 / 5.00	1676 / 5.86	1762 / 6.76			
5500	1454 / 3.74	1544 / 4.53	1628 / 5.35	1709 / 6.22	1789 / 7.13				
6050	1600 / 4.98	1681 / 5.83	1759 / 6.73						
6600	1745 / 6.46								

Max Sizeable RPM = 1800 RPM. Table shown extended beyond this point for reference only.

Motor 00312ET3H213T-S has an rpm range of 900 to 1150.

Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.

Motor 00318OT3H182T-S has an rpm range of 900 to 1750.

Motor 00512ET3H215T-W22 has an rpm range of 900 to 1150.

Motor 00512OT3H215T-S has an rpm range of 900 to 1150.

Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.

Motor 00518OT3H184T-S has an rpm range of 900 to 1750.

Motor 00718ET3H213T-W22 has an rpm range of 900 to 1750.

Motor 00718OT3H213T-S has an rpm range of 900 to 1750.

Motor DHP0056 has an rpm range of 900 to 1165.

Motor DTP0034 has an rpm range of 900 to 1755.

Motor DTP0034-50HZ has an rpm range of 900 to 1438.

Motor DTP0036 has an rpm range of 900 to 1150.

Motor DTP0054 has an rpm range of 900 to 1750.

Motor DTP0054-50 has an rpm range of 900 to 1435.

Motor DTP0056 has an rpm range of 900 to 1150.

Motor DTP7/54 has an rpm range of 900 to 1750.

Motor DTP7/54-50 has an rpm range of 900 to 1470.

Motor GP0034 has an rpm range of 900 to 1800.

Motor GP0034-50 has an rpm range of 900 to 1440.

Motor GP0036 has an rpm range of 900 to 1150.

Motor GP0054 has an rpm range of 900 to 1800.

Motor GP0054-50 has an rpm range of 900 to 1440.

Motor GP0056 has an rpm range of 900 to 1150.

Motor GP7/54 has an rpm range of 900 to 1800.

Motor GP7/54-50 has an rpm range of 900 to 1440.

Motor NP0056 has an rpm range of 900 to 1150.