

# RTU3-I.400HE-18-FA

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1900				957 / 0.68	1050 / 0.88	1137 / 1.11	1220 / 1.35	1300 / 1.59	1376 / 1.85	1448 / 2.11	1519 / 2.37	1586 / 2.64	1651 / 2.91	1713 / 3.19	1774 / 3.47
2210			936 / 0.64	1024 / 0.84	1108 / 1.05	1189 / 1.29	1266 / 1.54	1340 / 1.81	1411 / 2.08	1480 / 2.37	1547 / 2.66	1612 / 2.96	1674 / 3.26	1735 / 3.57	1794 / 3.88
2520		934 / 0.64	1018 / 0.83	1099 / 1.04	1175 / 1.26	1249 / 1.51	1321 / 1.77	1389 / 2.05	1457 / 2.35	1522 / 2.65	1585 / 2.96	1646 / 3.28	1705 / 3.61	1763 / 3.94	1821 / 4.29
2830	952 / 0.65	1029 / 0.86	1105 / 1.07	1178 / 1.28	1249 / 1.52	1317 / 1.77	1383 / 2.05	1448 / 2.34	1510 / 2.64	1571 / 2.96	1630 / 3.29	1689 / 3.63	1746 / 3.98	1801 / 4.34	1856 / 4.70
3140	1056 / 0.89	1125 / 1.12	1194 / 1.35	1262 / 1.58	1327 / 1.83	1390 / 2.10	1452 / 2.38	1512 / 2.68	1571 / 2.99	1628 / 3.32	1684 / 3.66	1739 / 4.02	1792 / 4.38	1846 / 4.76	
3450	1160 / 1.18	1224 / 1.44	1286 / 1.68	1348 / 1.94	1409 / 2.20	1467 / 2.48	1525 / 2.77	1582 / 3.08	1637 / 3.40	1691 / 3.74	1743 / 4.09	1796 / 4.46	1847 / 4.83		
3760	1265 / 1.53	1323 / 1.81	1381 / 2.08	1438 / 2.35	1494 / 2.63	1549 / 2.92	1603 / 3.23	1656 / 3.54	1708 / 3.88	1759 / 4.23	1809 / 4.59	1858 / 4.96			
4070	1369 / 1.94	1423 / 2.24	1476 / 2.54	1530 / 2.83	1582 / 3.13	1633 / 3.44	1684 / 3.75	1733 / 4.08	1782 / 4.42	1831 / 4.78					
4380	1473 / 2.42	1523 / 2.74	1573 / 3.06	1622 / 3.37	1671 / 3.69	1720 / 4.02	1768 / 4.35	1814 / 4.69							
4690	1578 / 2.97	1624 / 3.32	1670 / 3.65	1717 / 3.99	1763 / 4.34	1809 / 4.68									
5000	1682 / 3.59	1725 / 3.97	1769 / 4.33	1813 / 4.70											

Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.

Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00218OT3H145T-S has an rpm range of 900 to 1750.

Motor 00312ET3H213T-S has an rpm range of 900 to 1150.

Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.

Motor 00318OT3H182T-S has an rpm range of 900 to 1750.

Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.

Motor 00518OT3H184T-S has an rpm range of 900 to 1750.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.

Motor DHP0026 has an rpm range of 900 to 1150.

Motor DTP0024 has an rpm range of 900 to 1740.

Motor DTP0024-50HZ has an rpm range of 900 to 1415.

Motor DTP0026 has an rpm range of 900 to 1150.

Motor DTP0034 has an rpm range of 900 to 1755.

Motor DTP0034-50HZ has an rpm range of 900 to 1438.

Motor DTP0054 has an rpm range of 900 to 1750.

Motor DTP0054-50 has an rpm range of 900 to 1435.

Motor GP0024 has an rpm range of 900 to 1740.

Motor GP0024-50 has an rpm range of 900 to 1440.

Motor GP0026 has an rpm range of 900 to 1150.

Motor GP0034 has an rpm range of 900 to 1800.

Motor GP0034-50 has an rpm range of 900 to 1440.

Motor GP0054 has an rpm range of 900 to 1800.

Motor GP0054-50 has an rpm range of 900 to 1440.

Motor NP0024 has an rpm range of 900 to 1740.

Motor NP0026 has an rpm range of 900 to 1150.

Motor NP0054 has an rpm range of 900 to 1745.