RTU4-24-FA

CFM	Static Pressure in Inches W.G.							
	0.000	0.500	1,000	1,500	2.000	2,500	3.000	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500			720 / 0.79	877 / 1.33	1008 / 1.94	1123 / 2.60	1226 / 3.30	
2000			732 / 0.90	886 / 1.51	1017 / 2.18	1133 / 2.91	1238 / 3.69	1333 / 4.51
2500			751 / 1.03	898 / 1.68	1027 / 2.40	1142 / 3.19	1246 / 4.04	1343 / 4.93
3000			778 / 1.18	917 / 1.87	1041 / 2.64	1153 / 3.48	1256 / 4.37	
3500			810 / 1.36	943 / 2.09	1061 / 2.90	1169 / 3.78	1269 / 4.72	
4000			847 / 1.58	973 / 2.34	1086 / 3.19	1190 / 4.11	1287 / 5.09	
4500		746 / 1.09	887 / 1.82	1007 / 2.63	1116 / 3.52	1216 / 4.48	1310 / 5.50	
5000		796 / 1.31	929 / 2.10	1045 / 2.97	1149 / 3.90	1245 / 4.89	1336 / 5.95	
5500	704 / 0.79	847 / 1.57	974 / 2.42	1085 / 3.34	1185 / 4.32	1278 / 5.35		
6000	768 / 1.02	900 / 1.86	1021 / 2.78	1127 / 3.76	1224 / 4.78	1314 / 5.87		
6500	832 / 1.30	954 / 2.20	1069 / 3.18	1171 / 4.22	1265 / 5.30			
7000	896 / 1.62	1009 / 2.58	1118 / 3.63	1217 / 4.73	1308 / 5.86			
7500	960 / 1.99	1066 / 3.02	1169 / 4.13	1264 / 5.29				
8000	1024 / 2.42	1123 / 3.51	1221 / 4.68	1313 / 5.90				

Max Sizeable RPM = 1350 RPM. Table shown extended beyond this point for reference only.

Motor 00512ET3H215T-W22 has an rpm range of 700 to 1150.

Motor 00518ET3H184T-W22 has an rpm range of 700 to 1350.

Motor 00518OT3H184T-S has an rpm range of 700 to 1350.

Motor 00712OT3H254T-S has an rpm range of 700 to 1150.

Motor 00718ET3H213T-W22 has an rpm range of 700 to 1350.

Motor 00718OT3H213T-S has an rpm range of 700 to 1350.

Motor 01018ET3H215T-W22 has an rpm range of 700 to 1350.

Motor 01018OT3H215T-S has an rpm range of 700 to 1350.

Motor DHP0056 has an rpm range of 700 to 1165.

Motor DTP0054 has an rpm range of 700 to 1350.

Motor DTP0054-50 has an rpm range of 700 to 1350.

Motor DTP0056 has an rpm range of 700 to 1150.

Motor DTP0104 has an rpm range of 700 to 1350.

Motor DTP0104-50 has an rpm range of 700 to 1350.

Motor DTP7/54 has an rpm range of 700 to 1350.

Motor DTP7/54-50 has an rpm range of 700 to 1350.

Motor GP0054 has an rpm range of 700 to 1350.

Motor GP0054-50 has an rpm range of 700 to 1350.

Motor GP0056 has an rpm range of 700 to 1150.

Motor GP0104 has an rpm range of 700 to 1350.

Motor GP0104-50 has an rpm range of 700 to 1350.

Motor GP7/54 has an rpm range of 700 to 1350.

Motor GP7/54-50 has an rpm range of 700 to 1350.

Motor NP0056 has an rpm range of 700 to 1150.