

# RTU4-E.1204-30-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
3750		514 / 0.61	676 / 1.31	801 / 2.12	908 / 3.02	1002 / 4.01	1087 / 5.05	1165 / 6.17	1239 / 7.34
4875		557 / 0.80	713 / 1.60	837 / 2.51	943 / 3.50	1036 / 4.58	1120 / 5.73	1198 / 6.94	1271 / 8.21
6000		608 / 1.04	752 / 1.94	874 / 2.95	978 / 4.04	1071 / 5.22	1155 / 6.46	1233 / 7.76	1305 / 9.13
7125	544 / 0.63	668 / 1.36	797 / 2.34	913 / 3.45	1016 / 4.65	1108 / 5.92	1191 / 7.26	1268 / 8.66	1340 / 10.12
8250	630 / 0.98	735 / 1.78	849 / 2.83	957 / 4.03	1055 / 5.32	1145 / 6.70	1228 / 8.14	1305 / 9.64	1376 / 11.20
9375	716 / 1.43	807 / 2.31	906 / 3.42	1004 / 4.68	1098 / 6.09	1185 / 7.56	1266 / 9.10	1342 / 10.71	1413 / 12.37
10500	801 / 2.01	882 / 2.96	970 / 4.14	1059 / 5.49	1146 / 6.96	1229 / 8.53	1307 / 10.17	1381 / 11.87	1451 / 13.63
11625	887 / 2.73	960 / 3.76	1038 / 5.00	1118 / 6.41	1198 / 7.96	1276 / 9.61	1351 / 11.34	1423 / 13.14	1491 / 15.01
12750	973 / 3.60	1039 / 4.71	1109 / 6.01	1181 / 7.49	1255 / 9.10	1328 / 10.83	1398 / 12.65	1467 / 14.55	1533 / 16.50
13875	1059 / 4.64	1119 / 5.83	1182 / 7.20	1248 / 8.74	1316 / 10.42	1383 / 12.21	1450 / 14.11	1515 / 16.09	1578 / 18.14
15000	1145 / 5.86	1200 / 7.13	1258 / 8.57	1318 / 10.18	1380 / 11.92	1443 / 13.78	1505 / 15.75	1567 / 17.81	

Max Sizeable RPM = 1600 RPM. Table shown extended beyond this point for reference only.

Motor 01012ET3H256T-W22 has an rpm range of 500 to 1150.

Motor 01012OT3H256T-S has an rpm range of 500 to 1150.

Motor 01512ET3H284T-W22 has an rpm range of 500 to 1150.

Motor 01512OT3H284T-W40 has an rpm range of 500 to 1150.

Motor 02012ET3E286T-W22 has an rpm range of 500 to 1175.

Motor 02012ET3H286T-W22 has an rpm range of 500 to 1150.

Motor 02012OT3H286T-W40 has an rpm range of 500 to 1150.

Motor DHP0206 has an rpm range of 500 to 1150.

Motor DTP0106 has an rpm range of 500 to 1150.

Motor DTP0156 has an rpm range of 500 to 1150.

Motor DTP0156-50 has an rpm range of 500 to 958.

Motor DTP0206 has an rpm range of 500 to 1150.

Motor DTP0206-50 has an rpm range of 500 to 958.

Motor NP0106 has an rpm range of 500 to 1150.

Motor NP0106-50 has an rpm range of 500 to 958.

Motor NP0156 has an rpm range of 500 to 1150.

Motor NP0156-50 has an rpm range of 500 to 958.

Motor NP0206 has an rpm range of 500 to 1150.

Motor NP0206-50 has an rpm range of 500 to 958.