

# RTU4-E.302-20-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500			860 / 0.66	1045 / 1.09	1203 / 1.58	1342 / 2.15	1466 / 2.77	1581 / 3.46	1685 / 4.20
2110			891 / 0.84	1063 / 1.33	1215 / 1.86	1353 / 2.44	1478 / 3.07	1594 / 3.75	
2720			951 / 1.07	1103 / 1.61	1243 / 2.21	1372 / 2.85	1492 / 3.52	1606 / 4.24	
3330		881 / 0.85	1030 / 1.37	1165 / 1.96	1291 / 2.61	1409 / 3.31	1521 / 4.05	1628 / 4.83	
3940	816 / 0.59	986 / 1.18	1121 / 1.76	1243 / 2.40	1357 / 3.10	1465 / 3.86	1568 / 4.65	1667 / 5.49	
4550	942 / 0.91	1095 / 1.59	1219 / 2.25	1331 / 2.95	1435 / 3.70	1534 / 4.50	1630 / 5.35		
5160	1068 / 1.33	1208 / 2.12	1322 / 2.85	1426 / 3.61	1523 / 4.41	1615 / 5.27			
5770	1194 / 1.85	1322 / 2.75	1429 / 3.57	1526 / 4.40	1617 / 5.27				
6380	1320 / 2.51	1438 / 3.52	1539 / 4.43	1630 / 5.33					
6990	1446 / 3.29	1556 / 4.42	1651 / 5.43						

Max Sizeable RPM = 1700 RPM. Table shown extended beyond this point for reference only.

Motor 00518ET3H184T-W22 has an rpm range of 800 to 1700.

Motor 00518OT3H184T-S has an rpm range of 800 to 1700.

Motor 00718ET3H213T-W22 has an rpm range of 800 to 1700.

Motor 00718OT3H213T-S has an rpm range of 800 to 1700.

Motor DHP0056 has an rpm range of 800 to 1165.

Motor DTP0054 has an rpm range of 800 to 1700.

Motor DTP0054-50 has an rpm range of 800 to 1435.

Motor DTP0056 has an rpm range of 800 to 1150.

Motor DTP7/54 has an rpm range of 800 to 1700.

Motor DTP7/54-50 has an rpm range of 800 to 1470.

Motor GP0054 has an rpm range of 800 to 1700.

Motor GP0054-50 has an rpm range of 800 to 1440.

Motor GP7/54 has an rpm range of 800 to 1700.

Motor GP7/54-50 has an rpm range of 800 to 1440.

Motor NP0054 has an rpm range of 800 to 1700.

Motor NP0056 has an rpm range of 800 to 1150.