

RTU4-E.452-30-FA

CFM	Static Pressure in Inches W.G.						
	0.000	0.500	1.000	1.500	2.000	2.500	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500			550 / 0.80	671 / 1.33	774 / 1.94	865 / 2.62	947 / 3.34
2560			559 / 1.08	679 / 1.75	781 / 2.48	871 / 3.27	952 / 4.10
3620			575 / 1.39	690 / 2.19	790 / 3.06	879 / 3.98	960 / 4.94
4680			605 / 1.76	710 / 2.67	805 / 3.66	891 / 4.71	971 / 5.82
5740		548 / 1.38	648 / 2.25	741 / 3.24	828 / 4.33	910 / 5.50	986 / 6.73
6800		613 / 1.91	701 / 2.89	784 / 3.96	862 / 5.13	937 / 6.39	
7860	553 / 1.22	680 / 2.58	761 / 3.68	835 / 4.85	905 / 6.10	974 / 7.44	
8920	627 / 1.79	749 / 3.41	824 / 4.66	891 / 5.93	956 / 7.27		
9980	701 / 2.50	818 / 4.42	889 / 5.82	952 / 7.21			
11040	776 / 3.38	889 / 5.62	956 / 7.19				

Max Sizeable RPM = 1000 RPM. Table shown extended beyond this point for reference only.

Motor 01012ET3H256T-W22 has an rpm range of 500 to 1000.

Motor 01012OT3H256T-S has an rpm range of 500 to 1000.

Motor 01512ET3H284T-W22 has an rpm range of 500 to 1000.

Motor 01512OT3H284T-W40 has an rpm range of 500 to 1000.

Motor 02012ET3H286T-W22 has an rpm range of 500 to 1000.

Motor 02012OT3H286T-W40 has an rpm range of 500 to 1000.

Motor DHP0206 has an rpm range of 500 to 1000.

Motor DTP0106 has an rpm range of 500 to 1000.

Motor DTP0156 has an rpm range of 500 to 1000.

Motor DTP0156-50 has an rpm range of 500 to 958.

Motor DTP0206 has an rpm range of 500 to 1000.

Motor DTP0206-50 has an rpm range of 500 to 958.

Motor NP0106 has an rpm range of 500 to 1000.

Motor NP0106-50 has an rpm range of 500 to 958.

Motor NP0156 has an rpm range of 500 to 1000.

Motor NP0156-50 has an rpm range of 500 to 958.

Motor NP0206 has an rpm range of 500 to 1000.

Motor NP0206-50 has an rpm range of 500 to 958.