

RTU4-E.602-20-FA

CFM	Static Pressure in Inches W.G.							
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000			883 / 0.80	1057 / 1.28	1212 / 1.81	1351 / 2.38	1477 / 2.98	1594 / 3.62
2550			933 / 1.00	1089 / 1.52	1232 / 2.11	1364 / 2.74	1487 / 3.41	1602 / 4.11
3100		842 / 0.74	1000 / 1.25	1140 / 1.82	1270 / 2.45	1392 / 3.13	1508 / 3.85	1616 / 4.61
3650		934 / 1.01	1077 / 1.56	1205 / 2.18	1324 / 2.85	1436 / 3.58	1543 / 4.35	1646 / 5.16
4200	882 / 0.76	1031 / 1.34	1162 / 1.96	1280 / 2.63	1390 / 3.35	1494 / 4.11	1593 / 4.93	1689 / 5.79
4750	998 / 1.10	1131 / 1.75	1251 / 2.43	1361 / 3.16	1464 / 3.93	1561 / 4.74	1654 / 5.60	
5300	1113 / 1.53	1233 / 2.25	1345 / 3.00	1448 / 3.78	1544 / 4.60	1635 / 5.47		
5850	1229 / 2.05	1338 / 2.85	1442 / 3.67	1538 / 4.51	1629 / 5.39			
6400	1345 / 2.69	1445 / 3.56	1541 / 4.44	1631 / 5.36				
6950	1460 / 3.45	1553 / 4.39	1642 / 5.34					
7500	1576 / 4.33	1661 / 5.34						

Max Sizeable RPM = 1700 RPM. Table shown extended beyond this point for reference only.

Motor 00518ET3H184T-W22 has an rpm range of 800 to 1700.

Motor 00518OT3H184T-S has an rpm range of 800 to 1700.

Motor 00718ET3H213T-W22 has an rpm range of 800 to 1700.

Motor 00718OT3H213T-S has an rpm range of 800 to 1700.

Motor DHP0056 has an rpm range of 800 to 1165.

Motor DTP0054 has an rpm range of 800 to 1700.

Motor DTP0054-50 has an rpm range of 800 to 1435.

Motor DTP0056 has an rpm range of 800 to 1150.

Motor DTP7/54 has an rpm range of 800 to 1700.

Motor DTP7/54-50 has an rpm range of 800 to 1470.

Motor GP0054 has an rpm range of 800 to 1700.

Motor GP0054-50 has an rpm range of 800 to 1440.

Motor GP7/54 has an rpm range of 800 to 1700.

Motor GP7/54-50 has an rpm range of 800 to 1440.

Motor NP0054 has an rpm range of 800 to 1700.

Motor NP0056 has an rpm range of 800 to 1150.