

RTU4-E.602-24-FA

| CFM | Static Pressure in Inches W.G. | | | | | | | | | | | | | | |
|------|--------------------------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|
| | 0.000 | 0.250 | 0.500 | 0.750 | 1.000 | 1.250 | 1.500 | 1.750 | 2.000 | 2.250 | 2.500 | 2.750 | 3.000 | 3.250 | 3.500 |
| | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP |
| 2000 | | | | | 736 / 0.91 | 815 / 1.21 | 888 / 1.52 | 956 / 1.85 | 1019 / 2.19 | 1079 / 2.55 | 1136 / 2.92 | 1189 / 3.30 | 1240 / 3.70 | 1289 / 4.10 | 1336 / 4.52 |
| 2700 | | | | | 766 / 1.11 | 841 / 1.43 | 910 / 1.78 | 975 / 2.14 | 1036 / 2.52 | 1094 / 2.92 | 1150 / 3.33 | 1203 / 3.76 | 1254 / 4.20 | 1302 / 4.65 | 1350 / 5.12 |
| 3400 | | | | 737 / 1.04 | 811 / 1.36 | 879 / 1.71 | 944 / 2.08 | 1004 / 2.48 | 1062 / 2.89 | 1118 / 3.32 | 1171 / 3.76 | 1223 / 4.23 | 1272 / 4.70 | 1319 / 5.19 | |
| 4100 | | | 721 / 0.98 | 796 / 1.32 | 865 / 1.68 | 929 / 2.06 | 989 / 2.46 | 1046 / 2.88 | 1100 / 3.32 | 1152 / 3.78 | 1203 / 4.26 | 1251 / 4.75 | 1298 / 5.25 | 1344 / 5.77 | |
| 4800 | | 714 / 0.93 | 791 / 1.30 | 861 / 1.68 | 926 / 2.07 | 985 / 2.49 | 1042 / 2.92 | 1095 / 3.38 | 1146 / 3.84 | 1196 / 4.33 | 1243 / 4.83 | 1289 / 5.35 | 1334 / 5.88 | | |
| 5500 | 727 / 0.89 | 796 / 1.27 | 866 / 1.68 | 930 / 2.11 | 991 / 2.55 | 1047 / 3.00 | 1100 / 3.47 | 1151 / 3.96 | 1199 / 4.46 | 1246 / 4.98 | 1291 / 5.51 | 1335 / 6.06 | | | |
| 6200 | 819 / 1.27 | 881 / 1.70 | 943 / 2.16 | 1003 / 2.63 | 1059 / 3.11 | 1113 / 3.61 | 1163 / 4.12 | 1211 / 4.64 | 1257 / 5.18 | 1302 / 5.73 | 1345 / 6.29 | | | | |
| 6900 | 911 / 1.76 | 965 / 2.22 | 1023 / 2.73 | 1078 / 3.25 | 1131 / 3.78 | 1181 / 4.32 | 1229 / 4.87 | 1275 / 5.43 | 1319 / 6.00 | | | | | | |
| 7600 | 1004 / 2.35 | 1054 / 2.87 | 1105 / 3.41 | 1156 / 3.97 | 1205 / 4.55 | 1252 / 5.13 | 1298 / 5.73 | 1342 / 6.33 | | | | | | | |
| 8300 | 1096 / 3.05 | 1142 / 3.62 | 1189 / 4.21 | 1235 / 4.82 | 1281 / 5.44 | 1326 / 6.07 | | | | | | | | | |
| 9000 | 1189 / 3.89 | 1231 / 4.51 | 1274 / 5.14 | 1317 / 5.79 | | | | | | | | | | | |

Max Sizeable RPM = 1350 RPM. Table shown extended beyond this point for reference only.

- Motor 00512ET3H215T-W22 has an rpm range of 700 to 1150.
- Motor 00518ET3H184T-W22 has an rpm range of 700 to 1350.
- Motor 00518OT3H184T-S has an rpm range of 700 to 1350.
- Motor 00712OT3H254T-S has an rpm range of 700 to 1150.
- Motor 00718ET3H213T-W22 has an rpm range of 700 to 1350.
- Motor 00718OT3H213T-S has an rpm range of 700 to 1350.
- Motor 01018ET3H215T-W22 has an rpm range of 700 to 1350.
- Motor 01018OT3H215T-S has an rpm range of 700 to 1350.
- Motor DHP0056 has an rpm range of 700 to 1165.
- Motor DTP0054 has an rpm range of 700 to 1350.
- Motor DTP0054-50 has an rpm range of 700 to 1350.
- Motor DTP0056 has an rpm range of 700 to 1150.
- Motor DTP0104 has an rpm range of 700 to 1350.
- Motor DTP0104-50 has an rpm range of 700 to 1350.
- Motor DTP7/54 has an rpm range of 700 to 1350.
- Motor DTP7/54-50 has an rpm range of 700 to 1350.
- Motor GP0054 has an rpm range of 700 to 1350.
- Motor GP0054-50 has an rpm range of 700 to 1350.
- Motor GP0056 has an rpm range of 700 to 1150.
- Motor GP0104 has an rpm range of 700 to 1350.
- Motor GP0104-50 has an rpm range of 700 to 1350.
- Motor GP7/54 has an rpm range of 700 to 1350.
- Motor GP7/54-50 has an rpm range of 700 to 1350.
- Motor NP0056 has an rpm range of 700 to 1150.