

**RTU4-E.604-28-FA**

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000				619 / 0.46	706 / 0.65	785 / 0.85	857 / 1.06	923 / 1.29	985 / 1.52	1044 / 1.76	1099 / 2.01	1152 / 2.27	1203 / 2.54	1251 / 2.81	1297 / 3.09
2700				647 / 0.57	728 / 0.79	803 / 1.02	872 / 1.26	936 / 1.52	996 / 1.78	1053 / 2.06	1108 / 2.34	1160 / 2.63	1210 / 2.93	1258 / 3.24	
3400			611 / 0.48	689 / 0.70	763 / 0.95	831 / 1.21	896 / 1.48	957 / 1.76	1015 / 2.06	1070 / 2.36	1123 / 2.68	1174 / 3.00	1222 / 3.33	1269 / 3.67	
4100		610 / 0.41	677 / 0.62	743 / 0.87	808 / 1.13	871 / 1.42	930 / 1.72	987 / 2.03	1042 / 2.35	1095 / 2.69	1145 / 3.03	1194 / 3.38	1241 / 3.74	1286 / 4.11	
4800	641 / 0.37	693 / 0.57	750 / 0.80	807 / 1.07	864 / 1.36	920 / 1.66	974 / 1.99	1027 / 2.33	1078 / 2.67	1127 / 3.04	1175 / 3.41	1222 / 3.79	1266 / 4.17		
5500	734 / 0.55	780 / 0.78	828 / 1.04	877 / 1.32	928 / 1.63	977 / 1.96	1027 / 2.30	1075 / 2.66	1122 / 3.04	1168 / 3.42	1213 / 3.82	1257 / 4.23	1299 / 4.64		
6200	827 / 0.79	868 / 1.04	910 / 1.32	953 / 1.63	998 / 1.95	1042 / 2.30	1086 / 2.67	1130 / 3.05	1173 / 3.45	1216 / 3.86	1258 / 4.28	1299 / 4.71			
6900	921 / 1.09	957 / 1.37	994 / 1.67	1033 / 1.99	1072 / 2.34	1112 / 2.71	1152 / 3.10	1192 / 3.50	1231 / 3.92	1271 / 4.35					
7600	1014 / 1.46	1047 / 1.76	1080 / 2.08	1115 / 2.43	1150 / 2.80	1186 / 3.19	1222 / 3.59	1259 / 4.02	1295 / 4.45						
8300	1108 / 1.90	1137 / 2.22	1168 / 2.57	1199 / 2.94	1231 / 3.33	1264 / 3.74	1297 / 4.17								
9000	1201 / 2.42	1228 / 2.77	1256 / 3.15	1285 / 3.54											

Max Sizeable RPM = 1300 RPM. Table shown extended beyond this point for reference only.

Motor 186734/A01-ECM-50-480-28 has an rpm range of 600 to 1300.

Motor 186734/A01-ECM-60-480-28 has an rpm range of 600 to 1300.

Motor 186737/A01-ECM-50-240-28 has an rpm range of 600 to 1300.

Motor 186737/A01-ECM-60-240-28 has an rpm range of 600 to 1300.