

# RTU4-E.604-30-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000					557 / 0.94	624 / 1.25	684 / 1.58	740 / 1.93	791 / 2.29	840 / 2.67	886 / 3.07	929 / 3.49	971 / 3.91
3000					562 / 1.19	625 / 1.55	683 / 1.93	737 / 2.33	788 / 2.75	836 / 3.18	882 / 3.63	925 / 4.10	966 / 4.58
4000				523 / 1.13	584 / 1.51	640 / 1.91	694 / 2.33	744 / 2.78	793 / 3.25	838 / 3.73	882 / 4.23	925 / 4.75	965 / 5.28
5000			507 / 1.09	565 / 1.49	618 / 1.91	669 / 2.35	718 / 2.82	764 / 3.32	809 / 3.83	851 / 4.35	893 / 4.90	933 / 5.47	972 / 6.04
6000		507 / 1.06	563 / 1.49	614 / 1.94	663 / 2.41	708 / 2.91	752 / 3.42	795 / 3.96	836 / 4.51	875 / 5.09	914 / 5.68	951 / 6.29	988 / 6.91
7000	518 / 1.05	573 / 1.51	623 / 2.00	669 / 2.51	713 / 3.03	755 / 3.58	795 / 4.15	834 / 4.73	872 / 5.33	908 / 5.95	944 / 6.59	979 / 7.24	
8000	592 / 1.57	640 / 2.09	685 / 2.64	728 / 3.20	768 / 3.79	806 / 4.39	844 / 5.01	879 / 5.64	914 / 6.30	948 / 6.96	982 / 7.65		
9000	666 / 2.23	709 / 2.82	750 / 3.43	789 / 4.05	826 / 4.69	862 / 5.35	896 / 6.03	930 / 6.72	962 / 7.42	994 / 8.14			
10000	740 / 3.06	779 / 3.71	816 / 4.38	852 / 5.07	887 / 5.77	920 / 6.49	952 / 7.22	983 / 7.96					
11000	813 / 4.07	849 / 4.78	884 / 5.52	917 / 6.26	949 / 7.03	980 / 7.80							
12000	887 / 5.28	921 / 6.06	953 / 6.85	983 / 7.66									

Max Sizeable RPM = 1000 RPM. Table shown extended beyond this point for reference only.

Motor 00712ET3H254T-W22 has an rpm range of 500 to 1000.

Motor 00712OT3E254T-W40 has an rpm range of 500 to 1000.

Motor 00712OT3H254T-S has an rpm range of 500 to 1000.

Motor 01012ET3H256T-W22 has an rpm range of 500 to 1000.

Motor 01012OT3H256T-S has an rpm range of 500 to 1000.

Motor 01512ET3H284T-W22 has an rpm range of 500 to 1000.

Motor 01512OT3H284T-W40 has an rpm range of 500 to 1000.

Motor 02012ET3H286T-W22 has an rpm range of 500 to 1000.

Motor 02012OT3H286T-W40 has an rpm range of 500 to 1000.

Motor DHP0206 has an rpm range of 500 to 1000.

Motor DTP0106 has an rpm range of 500 to 1000.

Motor DTP0156 has an rpm range of 500 to 1000.

Motor DTP0156-50 has an rpm range of 500 to 958.

Motor DTP0206 has an rpm range of 500 to 1000.

Motor DTP0206-50 has an rpm range of 500 to 958.

Motor DTP7/56 has an rpm range of 500 to 1000.

Motor DTP7/56-50 has an rpm range of 500 to 958.

Motor NP0106 has an rpm range of 500 to 1000.

Motor NP0106-50 has an rpm range of 500 to 958.

Motor NP0156 has an rpm range of 500 to 1000.

Motor NP0156-50 has an rpm range of 500 to 958.

Motor NP0206 has an rpm range of 500 to 1000.

Motor NP0206-50 has an rpm range of 500 to 958.

Motor NP7/56 has an rpm range of 500 to 1000.

Motor NP7/56-50 has an rpm range of 500 to 958.