

RTU4-E.606-30-FA

CFM	Static Pressure in Inches W.G.													
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	
2000					557 / 0.94	624 / 1.25	684 / 1.58	740 / 1.93	791 / 2.29	840 / 2.67	886 / 3.07	929 / 3.49	971 / 3.91	
3000					562 / 1.19	625 / 1.55	683 / 1.93	737 / 2.33	788 / 2.75	836 / 3.18	882 / 3.63	925 / 4.10	966 / 4.58	
4000				523 / 1.13	584 / 1.51	640 / 1.91	694 / 2.33	744 / 2.78	793 / 3.25	838 / 3.73	882 / 4.23	925 / 4.75	965 / 5.28	
5000			507 / 1.09	565 / 1.49	618 / 1.91	669 / 2.35	718 / 2.82	764 / 3.32	809 / 3.83	851 / 4.35	893 / 4.90	933 / 5.47	972 / 6.04	
6000		507 / 1.06	563 / 1.49	614 / 1.94	663 / 2.41	708 / 2.91	752 / 3.42	795 / 3.96	836 / 4.51	875 / 5.09	914 / 5.68	951 / 6.29	988 / 6.91	
7000	518 / 1.05	573 / 1.51	623 / 2.00	669 / 2.51	713 / 3.03	755 / 3.58	795 / 4.15	834 / 4.73	872 / 5.33	908 / 5.95	944 / 6.59	979 / 7.24		
8000	592 / 1.57	640 / 2.09	685 / 2.64	728 / 3.20	768 / 3.79	806 / 4.39	844 / 5.01	879 / 5.64	914 / 6.30	948 / 6.96	982 / 7.65			
9000	666 / 2.23	709 / 2.82	750 / 3.43	789 / 4.05	826 / 4.69	862 / 5.35	896 / 6.03	930 / 6.72	962 / 7.42	994 / 8.14				
10000	740 / 3.06	779 / 3.71	816 / 4.38	852 / 5.07	887 / 5.77	920 / 6.49	952 / 7.22	983 / 7.96						
11000	813 / 4.07	849 / 4.78	884 / 5.52	917 / 6.26	949 / 7.03	980 / 7.80								
12000	887 / 5.28	921 / 6.06	953 / 6.85	983 / 7.66										

Max Sizeable RPM = 1000 RPM. Table shown extended beyond this point for reference only.

- Motor 01012ET3H256T-W22 has an rpm range of 500 to 1000.
- Motor 01012OT3H256T-S has an rpm range of 500 to 1000.
- Motor 01512ET3H284T-W22 has an rpm range of 500 to 1000.
- Motor 01512OT3H284T-W40 has an rpm range of 500 to 1000.
- Motor 02012ET3H286T-W22 has an rpm range of 500 to 1000.
- Motor 02012OT3H286T-W40 has an rpm range of 500 to 1000.
- Motor DHP0206 has an rpm range of 500 to 1000.
- Motor DTP0106 has an rpm range of 500 to 1000.
- Motor DTP0156 has an rpm range of 500 to 1000.
- Motor DTP0156-50 has an rpm range of 500 to 958.
- Motor DTP0206 has an rpm range of 500 to 1000.
- Motor DTP0206-50 has an rpm range of 500 to 958.
- Motor NP0106 has an rpm range of 500 to 1000.
- Motor NP0106-50 has an rpm range of 500 to 958.
- Motor NP0156 has an rpm range of 500 to 1000.
- Motor NP0156-50 has an rpm range of 500 to 958.
- Motor NP0206 has an rpm range of 500 to 1000.
- Motor NP0206-50 has an rpm range of 500 to 958.