

RTU4-I.300-30-FA

CFM	Static Pressure in Inches W.G.													
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500					558 / 0.86	622 / 1.16	680 / 1.47	733 / 1.81	782 / 2.16	829 / 2.53	874 / 2.93	916 / 3.33	956 / 3.75	994 / 4.18
2500				503 / 0.82	573 / 1.13	635 / 1.47	692 / 1.84	745 / 2.22	794 / 2.63	840 / 3.05	884 / 3.49	925 / 3.95	965 / 4.42	
3500				535 / 1.14	598 / 1.50	657 / 1.89	711 / 2.30	762 / 2.73	809 / 3.18	855 / 3.66	898 / 4.14	939 / 4.65	978 / 5.17	
4500			525 / 1.19	583 / 1.58	637 / 1.99	690 / 2.43	740 / 2.89	787 / 3.38	832 / 3.88	876 / 4.40	917 / 4.93	957 / 5.48	996 / 6.05	
5500		539 / 1.30	592 / 1.73	642 / 2.18	690 / 2.65	736 / 3.14	780 / 3.65	823 / 4.19	865 / 4.74	905 / 5.31	945 / 5.89	982 / 6.49		
6500	565 / 1.49	618 / 1.96	665 / 2.45	708 / 2.96	751 / 3.49	791 / 4.04	831 / 4.61	870 / 5.19	908 / 5.80	945 / 6.42	981 / 7.05			
7500	652 / 2.28	699 / 2.83	741 / 3.38	780 / 3.96	818 / 4.55	854 / 5.15	890 / 5.78	925 / 6.42	959 / 7.08	993 / 7.76				
8500	739 / 3.32	781 / 3.94	819 / 4.56	855 / 5.20	889 / 5.86	922 / 6.53	955 / 7.21	987 / 7.91						
9500	826 / 4.64	864 / 5.32	899 / 6.02	931 / 6.72	963 / 7.44	994 / 8.18								
10500	912 / 6.26	947 / 7.02	979 / 7.78											
11500	999 / 8.23													

Max Sizeable RPM = 1000 RPM. Table shown extended beyond this point for reference only.

- Motor 00712ET3H254T-W22 has an rpm range of 500 to 1000.
- Motor 00712OT3E254T-W40 has an rpm range of 500 to 1000.
- Motor 00712OT3H254T-S has an rpm range of 500 to 1000.
- Motor 01012ET3H256T-W22 has an rpm range of 500 to 1000.
- Motor 01012OT3H256T-S has an rpm range of 500 to 1000.
- Motor 01512ET3H284T-W22 has an rpm range of 500 to 1000.
- Motor 01512OT3H284T-W40 has an rpm range of 500 to 1000.
- Motor 02012ET3H286T-W22 has an rpm range of 500 to 1000.
- Motor 02012OT3H286T-W40 has an rpm range of 500 to 1000.
- Motor DHP0206 has an rpm range of 500 to 1000.
- Motor DTP0106 has an rpm range of 500 to 1000.
- Motor DTP0156 has an rpm range of 500 to 1000.
- Motor DTP0156-50 has an rpm range of 500 to 958.
- Motor DTP0206 has an rpm range of 500 to 1000.
- Motor DTP0206-50 has an rpm range of 500 to 958.
- Motor DTP7/56 has an rpm range of 500 to 1000.
- Motor DTP7/56-50 has an rpm range of 500 to 958.
- Motor NP0106 has an rpm range of 500 to 1000.
- Motor NP0106-50 has an rpm range of 500 to 958.
- Motor NP0156 has an rpm range of 500 to 1000.
- Motor NP0156-50 has an rpm range of 500 to 958.
- Motor NP0206 has an rpm range of 500 to 1000.
- Motor NP0206-50 has an rpm range of 500 to 958.
- Motor NP7/56 has an rpm range of 500 to 1000.
- Motor NP7/56-50 has an rpm range of 500 to 958.