

RTU4-I.300-30-FA

CFM	Static Pressure in Inches W.G.									
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2500			656 / 1.12	781 / 1.85	885 / 2.64					
3500		545 / 0.71	697 / 1.41	820 / 2.24	926 / 3.15	1019 / 4.15	1103 / 5.20	1179 / 6.30	1249 / 7.43	1314 / 8.60
4500		602 / 0.98	747 / 1.79	864 / 2.70	966 / 3.71	1058 / 4.80	1142 / 5.96	1220 / 7.19	1292 / 8.47	1360 / 9.80
5500	539 / 0.72	665 / 1.35	802 / 2.28	914 / 3.29	1013 / 4.38	1101 / 5.55	1183 / 6.80	1259 / 8.12	1331 / 9.50	1399 / 10.94
6500	637 / 1.19	737 / 1.85	860 / 2.86	969 / 4.00	1064 / 5.19	1149 / 6.46	1229 / 7.79	1303 / 9.19	1373 / 10.66	1439 / 12.18
7500	735 / 1.82	816 / 2.52	922 / 3.58	1026 / 4.83	1118 / 6.15	1202 / 7.52	1279 / 8.95	1351 / 10.44	1419 / 11.99	1483 / 13.59
8500	833 / 2.65	902 / 3.40	991 / 4.48	1086 / 5.81	1175 / 7.24	1256 / 8.74	1332 / 10.28	1402 / 11.88	1468 / 13.51	1531 / 15.21
9500	931 / 3.71	991 / 4.50	1066 / 5.60	1150 / 6.97	1234 / 8.50	1313 / 10.12	1387 / 11.78	1456 / 13.49	1521 / 15.25	1582 / 17.04
10500	1030 / 5.00	1082 / 5.85	1146 / 6.97	1220 / 8.36	1297 / 9.96	1373 / 11.68	1444 / 13.47	1511 / 15.30	1575 / 17.17	
11500	1128 / 6.57	1174 / 7.48	1230 / 8.63	1295 / 10.03	1364 / 11.67	1435 / 13.46	1503 / 15.35	1569 / 17.30		

Max Sizeable RPM = 1600 RPM. Table shown extended beyond this point for reference only.

- Motor 00712ET3H254T-W22 has an rpm range of 500 to 1150.
- Motor 00712OT3H254T-S has an rpm range of 500 to 1150.
- Motor 01012ET3H256T-W22 has an rpm range of 500 to 1150.
- Motor 01012OT3H256T-S has an rpm range of 500 to 1150.
- Motor 01512ET3H284T-W22 has an rpm range of 500 to 1150.
- Motor 01512OT3H284T-W40 has an rpm range of 500 to 1150.
- Motor 02012ET3E286T-W22 has an rpm range of 500 to 1175.
- Motor 02012ET3H286T-W22 has an rpm range of 500 to 1150.
- Motor 02012OT3H286T-W40 has an rpm range of 500 to 1150.
- Motor DHP0206 has an rpm range of 500 to 1150.
- Motor DTP0106 has an rpm range of 500 to 1150.
- Motor DTP0156 has an rpm range of 500 to 1150.
- Motor DTP0156-50 has an rpm range of 500 to 958.
- Motor DTP0206 has an rpm range of 500 to 1150.
- Motor DTP0206-50 has an rpm range of 500 to 958.
- Motor DTP7/56 has an rpm range of 500 to 1150.
- Motor DTP7/56-50 has an rpm range of 500 to 958.
- Motor NP0106 has an rpm range of 500 to 1150.
- Motor NP0106-50 has an rpm range of 500 to 958.
- Motor NP0156 has an rpm range of 500 to 1150.
- Motor NP0156-50 has an rpm range of 500 to 958.
- Motor NP0206 has an rpm range of 500 to 1150.
- Motor NP0206-50 has an rpm range of 500 to 958.
- Motor NP7/56 has an rpm range of 500 to 1150.
- Motor NP7/56-50 has an rpm range of 500 to 958.