

SA28Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
6000	849 / 0.99	890 / 1.26	934 / 1.55	979 / 1.87	1025 / 2.22	1071 / 2.58	1116 / 2.96	1161 / 3.35	1205 / 3.76	1248 / 4.18	1290 / 4.61	1331 / 5.04	1371 / 5.49
6500	920 / 1.26	958 / 1.54	998 / 1.86	1039 / 2.19	1081 / 2.56	1124 / 2.94	1166 / 3.33	1208 / 3.75	1249 / 4.17	1290 / 4.61	1330 / 5.05	1369 / 5.51	
7000	990 / 1.57	1025 / 1.88	1062 / 2.21	1101 / 2.56	1139 / 2.94	1179 / 3.34	1218 / 3.75	1257 / 4.18	1296 / 4.62	1334 / 5.08	1372 / 5.55		
7500	1061 / 1.93	1094 / 2.26	1128 / 2.61	1163 / 2.98	1199 / 3.37	1236 / 3.79	1272 / 4.22	1309 / 4.67	1346 / 5.12	1382 / 5.60			
8000	1132 / 2.35	1162 / 2.69	1194 / 3.06	1227 / 3.45	1260 / 3.86	1294 / 4.29	1329 / 4.74	1363 / 5.20	1398 / 5.68				
8500	1202 / 2.81	1231 / 3.18	1261 / 3.57	1292 / 3.97	1323 / 4.40	1355 / 4.85	1387 / 5.31						
9000	1273 / 3.34	1300 / 3.72	1328 / 4.13	1357 / 4.56	1386 / 5.00								
9500	1344 / 3.93	1369 / 4.33	1396 / 4.76										

Max Sizeable RPM = 1400 RPM. Table shown extended beyond this point for reference only.

Motor 186734/A01-ECM-50-480-28 has an rpm range of 300 to 1300.

Motor 186734/A01-ECM-60-480-28 has an rpm range of 300 to 1300.

Motor 186737/A01-ECM-50-240-28 has an rpm range of 300 to 1300.

Motor 186737/A01-ECM-60-240-28 has an rpm range of 300 to 1300.

Motor 186739/A01-ECM-50-480-28 has an rpm range of 300 to 1400.

Motor 186739/A01-ECM-60-480-28 has an rpm range of 300 to 1400.